


DCP-9040CN DCP-9042CDN



Before you can use the machine, you must set up the hardware and install the driver. Please read this 'Quick Setup Guide' for proper set up and installation instructions.

STEP 1

Setting Up the Machine



STEP 2

Installing the Driver & Software

Setup is Complete!

Keep this 'Quick Setup Guide' and the supplied CD-ROM in a convenient place for quick and easy reference at all times.






Warning	Electrical Hazard	Hot Surface	Caution
Warnings tell you what to do to prevent possible personal injury.	Electrical Hazard icons alert you to a possible electrical shock.	Hot Surface icons warn you not to touch machine parts that are hot.	Cautions specify procedures you must follow or avoid to prevent possible damage to the machine.
Marion Setup	Note	User's Guide, Software User's Guide or Network User's Guide	
Improper Setup icons alert you to devices and operations that are not compatible with the machine.	Notes tell you how you should respond to a situation that may arise or give tips about how the current operation works with other features.	Indicates reference to the User's Guide, Software User's Guide or Network User's Guide which is on the CD-ROM we have supplied.	


Getting Started Carton components ______2 STEP 1 - Setting Up the Machine Remove the packing materials from the machine5 Installing the toner cartridges 6 Load paper in the paper tray6 STEP 2 – Installing the Driver & Software Windows[®] For USB Interface Cable Users For Network Interface Users For Windows Server® 2003, see the Network User's Guide on the CD-ROM. Macintosh[®] For Network Users Setting your IP address, Subnet Mask and Gateway using BRAdmin Light23 BRAdmin Light utility (For Mac OS® X users)......24 Setting your IP address, Subnet Mask and Gateway using BRAdmin Light24 **Uninstalling the 'MFL-Pro Suite' Consumables and Options**

Carton components



- 1 Automatic Document Feeder (ADF)
- 2 Control Panel
- 3 Front Cover Release Button
- 4 Front Cover
- 5 Paper Tray

- 6 Power Switch
- 7 ADF Document Output Support Flap
- 8 Document Cover
- 9 Face-down Output Tray Support
- 10 Multi-purpose tray (MP tray)



Carton components may vary from one country to another.

Save all packing materials and the carton in case for any reason you must ship your printer.

Australia & New Zealand users:

Hong Kong, Malaysia & Singapore users:





The mains plug supplied with this machine is a grounded three pin plug. Make sure that the AC socket will accept this grounded three pin plug. This machine must be grounded, If in doubt, call a qualified electrician.

Philippines & Thailand users:



The mains plug supplied with this machine is a side grounded two pin plug. Make sure that the AC socket will accept this side grounded two pin plug. This machine must be grounded, If in doubt, call a qualified electrician.


- To ensure safe operation the supplied plug must be inserted only into a standard power outlet that is properly grounded through the standard electrical wiring. Non grounded equipment may cause an electrical shock hazard, and may cause excessive electrical noise radiation.
- The interface cable is not a standard accessory. Please purchase the appropriate interface cable for the interface you intend to use (USB or Network).
- DO NOT connect the interface cable at this time. Connecting the interface cable is done during the software installation process.
- USB interface cable

 Please make sure you use a USB 2.0 interface cable that is no longer than 2 metres. When you use a USB cable, make sure you connect it to the USB port of your computer and not to a USB port on a keyboard or non-powered USB hub.
- Network cable
 Use a straight-through Category5 (or greater) twisted-pair cable for 10BASE-T or 100BASE-TX Fast Ethernet
 Network.



Control panel

DCP-9040CN and DCP-9042CDN have similar control keys.



- 1 Copy keys
- 2 LCD (Liquid Crystal Display)
- 3 Data LED
- 4 Menu keys
- 5 Numeric keys


- 6 Stop/Exit key
- 7 Start keys
- 8 Print keys
- 9 Scan key



For the details of the control panel, see Control panel overview in Chapter 1 of the User's Guide.



This machine is heavy and weighs 72.6 lb (32.8 kg). To prevent injuries use at least two people to lift the machine. Be careful not to pinch your fingers when you set the machine back down.



EP 1 Setting Up the Machine

Remove the packing materials from the machine


Important

Save all packing materials and the carton in case you have to ship your machine.


Name of the last o DO NOT plug in the AC power cord yet.




- Remove the packing tape from the outside of the machine.
- Press the front cover release button and open the front cover.




Remove the four pieces of orange packing material as shown in the illustration below.



Hold the green handle of the drum unit. Lift the drum unit up and then pull it out until it stops.




Remove the orange packing material as shown in the illustration below.



Installing the toner cartridges


Unpack the toner cartridges and gently shake each toner cartridge from side to side 5 to 6 times.



Pull off the protective cover.




Hold the handle of the toner cartridge and slide it into the drum unit. Make sure that you match the toner cartridge colour to the same colour label on the drum unit, and make sure that you fold down the toner cartridge handle (1) once the toner cartridge is in place.




- C Cyan
- M Magenta
- Y Yellow
- K Black

- Repeat steps 1 through 3 for the remaining toner cartridges.
- Put the drum unit back into the machine.



6 Close the front cover of the machine.




Load paper in the paper tray

Name of the last o

DO NOT connect the interface cable. Connecting the interface cable is done during the software installation process.




Pull the paper tray completely out of the machine.




Setting Up the Machine


While pressing the green paper-guide release lever (1), slide the paper guides to fit the paper size. Make sure that the guides are firmly in the slots.




Fan the stack of paper well to avoid paper jams and misfeeds.



4 Put paper in the paper tray. Make sure that the paper is flat in the tray and below the maximum paper mark.




5 Put the paper tray firmly back into the machine.




4 Install the power cord

Make sure that the machine's power switch is off. Remove the label covering the AC power inlet.



2 Connect the AC power cord to the machine.



Plug the AC power cord into an AC outlet. Turn the power switch on.





5 Setting the LCD contrast

You can change the contrast to help the LCD look lighter or darker.

- 1 Press Menu.
- Press 1.
- Press 6.
- 4 Press to increase the contrast.

─OR—
Press to decrease the contrast.
Press **OK**.

5 Press Stop/Exit.

Supplied CD-ROM 'MFL-Pro Suite'



Supplied CD-ROM 'MFL-Pro Suite'

Windows[®]





🔯 Install MFL-Pro Suite

You can install the MFL-Pro Suite software and multifunction drivers.



🔝 Install Other Drivers or Utilities

You can install additional MFL-Pro Suite software utilities.



Documentation

View the User's Guide, Software User's Guide and Network User's Guide in HTML format. You can also view the manuals in PDF format by accessing the Brother Solutions Center. (Internet access required) The Software User's Guide and Network User's Guide include instructions for features available when connected to a computer. (eg. printing, scanning and networking details)



On-Line Registration

Register your machine on the Brother product Registration Page.



Brother Solutions Center

Access the Brother Solutions Center for FAQs, User's Guide, driver updates and tips for using your machine. (Internet access required)



Supplies Information

Visit our site for original/genuine Brother supplies at http://www.brother.com/original/



Repair MFL-Pro Suite (For USB users only)

If an error occurred during the installation of the MFL-Pro Suite, use this selection to automatically repair and re-install the MFL-Pro Suite.



MFL-Pro Suite includes the Printer Driver. Scanner Driver, Brother ControlCenter3, ScanSoft™ PaperPort™ 11SE with OCR by NUANCE™. ScanSoft™ PaperPort™ 11SE is a document management application for scanning and viewing documents.

Macintosh[®]





Start Here OSX

You can install the MFL-Pro Suite that includes the printer driver, scanner driver and the Brother ControlCenter2 and BRAdmin Light for Mac OS® X 10.2.4 or greater.



Documentation

View the User's Guide, Software User's Guide and Network User's Guide in HTML format. You can also view the manuals in PDF format by accessing the Brother Solutions Center. (Internet access required) The Software User's Guide and Network User's Guide include instructions for features available when connected to a computer. (eg. printing, scanning and networking details)



@ Brother Solutions Center

Access the Brother Solutions Center for FAQs, User's Guide, driver updates and tips for using your machine. (Internet access required)



Presto!® PageManager®

You can install Presto!® PageManager® to add OCR capability to the Brother ControlCenter2 and easily scan, share and organize photos and documents.



On-Line Registration

Register your machine on the Brother product Registration Page.



Utilities

You can find the following additional Utilities from this

- Presto!® PageManager® Uninstaller
- BRAdmin Light

STEP 2 Installing the Driver & Software

Follow the instructions on this page for your operating system and interface. For the latest drivers, documentation, and to find the best solution for your problem, access the Brother Solutions Center directly from the CD-ROM / Driver or visit http://solutions.brother.com/.

Windows®





For Windows Server® 2003, see Chapter 5 of the Network User's Guide

Macintosh®



For USB Interface Cable Users...... 18

For Network Interface Users.....




For USB Interface Cable Users (For Windows® 2000 Professional/XP/ XP Professional x64 Edition/Windows Vista®)

Important

Make sure that you have finished the instructions from step 1 Setting Up the Machine on pages 5 through 7.



- Please close any applications running before installing the MFL-Pro Suite.
- The supplied CD-ROM includes ScanSoft™ PaperPort™ 11SE. This software supports Windows® 2000 (SP4 or greater), XP (SP2 or greater), XP Professional x64 Edition and Windows Vista® only. Please update to the latest Windows® Service Pack before installing MFL-Pro Suite.
- Turn off and unplug the machine from the AC outlet and disconnect it from your computer, if you already connected an interface cable.



- Turn on your computer. (You must be logged on with administrator rights.)
- Put the supplied CD-ROM for Windows® into your CD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.




The CD-ROM main menu will appear. Click Install MFL-Pro Suite.





- If this window does not appear, use Windows[®] Explorer to run the start.exe program from the root folder of the Brother CD-ROM.
- For Windows Vista[®], when the User Account Control screen appears, click Allow.



5 After reading and accepting the ScanSoft™ PaperPort™ 11SE License Agreement, click Yes.




The installation of ScanSoft™ PaperPort™ 11SE will automatically start and is followed by the installation of MFL-Pro Suite.

When the Brother MFL-Pro Suite Software License Agreement window appears, click **Yes** if you agree to the Software License Agreement.



Choose Local Connection, and then click Next. The installation will continue.







If you want to install the PS driver (Brother's BR-Script Driver), choose **Custom Install** and then follow the on-screen instructions. When the **Select Features** screen appears, check **PS Printer Driver**, and then continue following the on-screen instructions.

When this screen appears, remove the label covering the USB port on the machine.

Connect the interface cable to your computer, and then connect it to the machine.





DO NOT connect the machine to a USB port on a keyboard or a non-powered USB hub. Brother recommends that you connect the machine directly to your computer.

Plug the AC power cord into an AC outlet. Turn the power switch on.





The installation of the Brother drivers will automatically start. The installation screens appear one after another, please wait for a while.

◯ Improper Setup

DO NOT try to cancel any of the screens during this installation.

10 When the On-Line Registration screen is displayed, make your selection and follow the on-screen instructions.



11 Click **Finish** to restart your computer. (You must be logged on with Administrator rights.)





- XML Paper Specification Printer Driver
 The XML Paper Specification Printer Driver is the
 most suitable driver when printing from the
 applications that use the XML Paper Specification
 documents. Please download the latest driver by
 accessing the Brother Solutions Center at
 http://solutions.brother.com/.
- After restarting the computer, the Installation
 Diagnostics will run automatically. If the
 installation is unsuccessful, the installation results
 window will be shown. If the Installation
 Diagnostics shows a failure, please follow the
 on-screen instruction or read on-line help and
 FAQs in Start/All Programs / Brother/
 DCP-XXXX.



The MFL-Pro Suite (including printer driver and scanner driver) has been installed and the installation is now complete.



For Network Interface Users (For Windows® 2000 Professional/XP/ XP Professional x64 Edition/Windows Vista®)


Important

Make sure that you have finished the instructions from step 1 Setting Up the Machine on pages 5 through 7.



The supplied CD-ROM includes ScanSoft™
PaperPort™ 11SE. This software supports
Windows® 2000 (SP4 or greater), XP (SP2 or greater), XP Professional x64 Edition and
Windows Vista® only. Please update to the latest
Windows® Service Pack before installing MFL-Pro
Suite.

- Turn off and unplug the machine from the AC outlet.
- Connect the network interface cable to the machine, and then connect it to your network.



Plug the AC power cord into an AC outlet. Turn the power switch on.






Turn on your computer. (You must be logged on with Administrator rights.) Close any applications running before installing the MFL-Pro Suite.



Before installation, if you are using personal firewall software, disable it. After the installation, restart your personal firewall software.

Put the supplied CD-ROM into your CD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.




The CD-ROM main menu will appear. Click Install MFL-Pro Suite.





- If this window does not appear, use Windows[®] Explorer to run the start.exe program from the root folder of the Brother CD-ROM.
- For Windows Vista[®], when the User Account Control screen appears, click **Allow**.



After reading and accepting the ScanSoft™ PaperPort™ 11SE License Agreement, click Yes.



The installation of ScanSoft™ PaperPort™ 11SE will automatically start and is followed by the installation of MFL-Pro Suite.

When the Brother MFL-Pro Suite Software License Agreement window appears, click **Yes** if you agree to the Software License Agreement.



Choose Network Connection, and then click Next.





If you want to install the PS driver (Brother's BR-Script Driver), choose **Custom Install** and then follow the on-screen instructions. When the **Select Features** screen appears, check **PS Printer Driver**, and then continue following the on-screen instructions.

10 If the machine is configured for your network, choose the machine from the list, and then click **Next**. This window will not appear if there is only one machine connected on the network, it will be chosen automatically.



If your machine shows **APIPA** in the **IP Address** field, click **Configure IP Address** and enter an **IP address** for your machine that is suitable for your network.



If the machine is not yet configured for use on your network, the following screen appears.



Click OK.

The **Configure IP Address** window will appear. Enter an **IP address** for your machine that is suitable for your network by following the onscreen instructions.

- 11 The installation of the Brother drivers will automatically start. The installation screens appear one after another, please wait for a while.
- **⊘** Improper Setup

DO NOT try to cancel any of the screens during this installation.



For Windows Vista[®], when this screen appears, click the check box and click **Install**.



12 When the Brother and ScanSoft on-line Registration screen is displayed, make your selection and follow the on-screen instructions.



13 Click **Finish** to restart your computer. (You must be logged on with Administrator rights.)





The MFL-Pro Suite has been installed and the installation is now complete.



- XML Paper Specification Printer Driver
 The XML Paper Specification Printer Driver is the
 most suitable driver when printing from the
 applications that use the XML Paper Specification
 documents. Please download the latest driver by
 accessing the Brother Solutions Center at
 http://solutions.brother.com/.
- MFL-Pro Suite includes the Network Printer Driver, Network Scanner Driver, Brother ControlCenter3, ScanSoft™ PaperPort™ 11SE. ScanSoft™ PaperPort™ 11SE is a document management application for viewing scanned documents.
- After restarting the computer, the Installation
 Diagnostics will run automatically. If the
 installation is unsuccessful, the installation results
 window will be shown. If the Diagnostics shows a
 failure, please follow the on-screen instructions or
 read the on-line help and FAQ's in
 Start/All Programs /Brother/DCP-XXXX.
- Once you are sure that you can print after the installation, restart your Firewall software.
- Firewall settings on your PC may reject the necessary network connection for Network Scanning.

Follow the instructions on the following page to configure your Windows[®] Firewall. If you are using personal firewall software, see the User's Guide for your software or contact the software manufacturer.

Firewall settings

Firewall settings on your PC may reject the necessary network connection for Network Scanning and Printing. If you are using the Windows[®] Firewall follow the instructions for Windows[®] XP SP2 or Windows Vista[®]. If you are using personal firewall software, see the User's Guide for your software or contact the software manufacturer.

- For Windows[®] XP SP2 users:
 - Click the Start button, Control Panel, Network and Internet Connections and then Windows Firewall.
 Make sure that Windows Firewall on the General tab is set to On.
 - 2 Click the **Advanced** tab and **Settings...** button.




- 3 Click the Add button.
- 4 Add port **54925** for network scanning by entering the information below:
 - 1. In Description of service:
 - Enter any description, for example "Brother Scanner".
 - 2. In Name or IP address (for example 192.168.0.12) of the computer hosting this service on your network:
 - Enter "Localhost".
 - 3. In External Port Number for this service:
 - Enter "54925".
 - 4. In Internal Port number for this service:
 - Enter "54925".
 - 5. Make sure **UDP** is selected.
 - 6. Click OK.



- 5 Click the Add button.
- 6 If you still have trouble with your network connection, click the **Add** button.
- 7 Add port 137 for network scanning and Network printing by entering the information below:
 - 1. In Description of service:
 - Enter any description, for example "Brother Network Print".
 - 2. In Name or IP address (for example 192.168.0.12) of the computer hosting this service on your network:
 - Enter "Localhost".
 - 3. In External Port Number for this service:
 - Enter "137".
 - 4. In Internal Port number for this service:
 - Enter "137".
 - 5. Make sure **UDP** is selected.
 - 6. Click OK.
- 8 Make sure that the new settings are added and checked, and then click **OK**.


- For Windows Vista[®] users:
 - Click the Start button, Control Panel, Network and Internet, Windows Firewall and click change settings.
 - When the User Account Control screen appears, do the following.
 - For Users who have administrator rights: Click **Continue**.



Users who do not have administrator rights: Enter the administrator password and click OK.




- 3 Make sure that Windows Firewall on the **General** tab is set to On.
- 4 Click the Exceptions tab.




5 Click the Add port... button.

- 6 To add port **54925** for network scanning, enter the information below:
 - 1. In **Name**: Enter any description, for example "Brother Scanner".
 - 2. In Port number: Enter "54925".
 - Make sure **UDP** is selected. Then, click **OK**.



- 7 Click the Add port... button.
- 8 Make sure that the new setting is added and is checked, and then click **OK**.
- 9 If you still have trouble with your network connection such as Network Scanning or Printing, check the File and Printer Sharing box in the Exceptions tab and then click OK.





For USB Interface Cable Users

For Mac OS® X 10.2.4 or greater


Important

Make sure that you have finished the instructions from step 1 Setting Up the Machine on pages 5 through 7.



For Mac OS^{\otimes} X 10.2.0 to 10.2.3 users, upgrade to Mac OS^{\otimes} X 10.2.4 or greater. (For the latest information for Mac OS^{\otimes} X, visit http://solutions.brother.com/)

Remove the label covering the USB port on the machine. Connect the interface cable to your computer, and then connect it to the machine.



Improper Setup

DO NOT connect the machine to a USB port on a keyboard or a non-powered USB hub. Brother recommends that you connect the machine directly to your computer.



Make sure that the machine is turned on by connecting the power cord.

Turn on your Macintosh[®].

Put the supplied CD-ROM into your CD-ROM drive.



Double-click the **Start Here OSX** icon to install. Follow the on-screen instructions.




Please wait, it will take a few seconds for the software to install. After the installation, click **Restart** to finish installing the software.



Please see the Software User's Guide on the CD-ROM to install the PS driver.

The Brother software will search for the Brother device. During this time the following screen will appear.




6 When this screen appears, click **OK**.



For Mac OS® X 10.3.x or greater users:
The MFL-Pro Suite, Brother printer driver,
scanner driver and Brother
ControlCenter2 have been installed and
the installation is now complete.
Go to step 11.

7 For Mac OS® X 10.2.4 to 10.2.8 users: Click **Add**.



Choose USB.



Choose your model name, and then click Add.




10 Click Print Center, then Quit Print Center.



The MFL-Pro Suite, Brother printer driver, scanner driver and Brother ControlCenter2 have been installed and the installation is now complete.

11 To install Presto!®PageManager®, double-click the **Presto! PageManager** icon and follow the on-screen instructions.





When Presto!®PageManager® is installed OCR capability is added to the Brother ControlCenter2. You can easily scan, share and organize photos and documents using Presto!® PageManager®.



Presto![®] PageManager[®] has been installed and the installation is now complete.




For Network Interface Users

For Mac OS® X 10.2.4 or greater

Important

Make sure that you have finished the instructions from step 1 Setting Up the Machine on pages 5 through 7.


Connect the network interface cable to the machine, and then connect it to your network.





Make sure that the machine is turned on by connecting the power cord.

- Turn on your Macintosh[®].
- 3 Put the supplied CD-ROM into your CD-ROM drive



Double-click the **Start Here OSX** icon to install. Follow the on-screen instructions.



Please wait, it will take a few seconds for the software to install. After the installation, click **Restart** to finish installing the software.



Please see the Network User's Guide on the CD-ROM to install the PS driver.

The Brother software will search for the Brother device. During this time the following screen will appear.

MFL-Pro Suite



 If the machine is configured for your network, choose the machine from the list, and then click OK. This window will not appear if there is only one machine connected on the network, it will be chosen automatically. Go to step 6.



• If this screen appears click OK.



Enter a name for your Macintosh[®] in **Display Name** up to 15 characters long and click **OK**. Go to step **6**.

The name can be any name you want.



 The name you enter will appear on the machine's LCD when you press the Scan key and choose a scan option. (For more information, see Network Scanning in the Software User's Guide on the CD-ROM.) 6 When this screen appears, click **OK**.



- For Mac OS® X 10.3.x or greater users:
 The MFL-Pro Suite, Brother printer driver,
 scanner driver and Brother
 ControlCenter2 have been installed and
 the installation is now complete.
 Go to step 11.
- For Mac OS® X 10.2.4 to 10.2.8 users: Click **Add**.




For Mac OS® X 10.2.4 to 10.2.8 users: Make the selection shown below.



9 Choose your model name, and then click Add.



10 Click Print Center, then Quit Print Center.



The MFL-Pro Suite, Brother printer driver, scanner driver and Brother ControlCenter2 have been installed and the installation is now complete.

11 To install Presto!®PageManager®, double-click the **Presto! PageManager** icon and follow the on-screen instructions.





When Presto!® PageManager® is installed OCR capability is added to the Brother ControlCenter2. You can easily scan, share and organize photos and documents using Presto!® PageManager®.



Presto![®] PageManager[®] has been installed and the installation is now complete.



BRAdmin Light utility (For Windows® users)

The BRAdmin Light is a utility for initial setup of Brother network connected devices. It also can search for Brother products on your network, view the status and configure basic network settings, such as IP address. For more information on BRAdmin Light, visit us at http://solutions.brother.com/.



If you require more advanced printer management, use the latest Brother BRAdmin Professional utility version that is available as a download from http://solutions.brother.com/.

Installing the BRAdmin Light configuration utility



The default password for the print server is 'access'. You can use BRAdmin Light to change this password.

Click Install Other Drivers or Utilities on the menu screen.



Click BRAdmin Light and follow the on-screen instructions.



Setting your IP address, Subnet Mask and Gateway using BRAdmin Light



If you have a DHCP/BOOTP/RARP server in your network, you don't have to do the following operation. The print server will automatically obtain its own IP address.

Start BRAdmin Light. It will search for new devices automatically.



2 Double-click the unconfigured device.



Choose **STATIC** for the **Boot Method**. Enter the **IP Address**, **Subnet Mask** and **Gateway**, and then click **OK**.



The address information will be saved to the machine.



BRAdmin Light utility (For Mac OS® X users)

The BRAdmin Light is a utility for initial setup of Brother network connected devices. It also can search for Brother products on your network, view the status and configure basic network settings, such as IP address from a computer running Mac OS[®] X 10.2.4 or greater.

The BRAdmin Light software will be installed automatically when you install the printer driver. If you have already installed the printer driver, you don't have to install it again. For more information on BRAdmin Light, visit us at http://solutions.brother.com/.

Setting your IP address, Subnet Mask and Gateway using BRAdmin Light



- If you have a DHCP/BOOTP/RARP server in your network, you don't have to do the following operation. The print server will automatically obtain its own IP address.
- Make sure that version 1.4.1_07 or later of Java™ client software is installed on your computer.
- The default password for the print server is 'access'. You can use BRAdmin Light to change this password.
- 1 Double-click the **Macintosh HD** icon on your desktop.





Choose Library, Printers, Brother and then Utilities.




Double-click the file **BRAdmin Light.jar** and run the software. BRAdmin Light will then search for new devices automatically.



Double-click the unconfigured device.



Choose **STATIC** for the **Boot Method**. Enter the **IP Address**, **Subnet Mask** and **Gateway**, and then click **OK**.



The address information will be saved to the machine.



Web Based Management (web browser)

The Brother print server is equipped with a web server that allows you to monitor its status or change some of its configuration settings, using HTTP (Hyper Text Transfer Protocol).



- The User Name is 'admin' and the default password is 'access'. You can use a web browser to change this password.
- We recommend Microsoft Internet Explorer 6.0[®]
 (or higher) or Firefox[®] 1.0 (or higher) for
 Windows® and Safari™ 1.0 for Macintosh[®].
 Please also make sure that JavaScript and
 cookies are always enabled in whichever
 browser you use. We recommend you upgrade
 to Safari™ 1.2 or higher to enable JavaScript.
 To use a web browser, you will need to know the
 IP address of the print server.
- 1 Open your browser.
- Type http://printer_ip_address / into your browser (Where "printer_ip_address" is the IP address of the printer or the print server name).





See Chapter 2 of the Network User's Guide on the CD-ROM.



Restoring the network settings to factory default

To restore all network settings of the internal Print/Scan server to factory default, please follow the steps below.

- Make sure the machine is not in use, then disconnect all the cables from the machine (except power cable).
- 2 Press Menu, 4, 0.
- 3 Press 1 to select Reset.
- 4 Press 1 to select Yes.
- The machine will restart. Re-connect cables once this is complete.

Uninstalling the 'MFL-Pro Suite'



Instructions on how to uninstall the MFL-Pro Suite software

Uninstalling for Windows

○ Improper Setup

DO NOT remove the USB cable (until step 3 of the uninstallation process).

Close all applications and all programs on task tray before uninstalling the MFL-Pro suite.

Start/All Programs/Brother/DCP-XXXX/Uninstall

- 1 Click Uninstall.
- Click **OK**.



Remove the USB cable and click **Finish**.





The MFL-Pro Suite has been uninstalled and the uninstallation is now complete.

Uninstalling for Macintosh

How to uninstall the Printer and Scanner Driver:

- Disconnect the USB cable between the Macintosh and your Brother device.
- 2 Reboot the Mac.
- 3 Log on as an "Administrator".
- Run the "Print Center" or
 "Printer Setup Utility"
 (from the Macintosh HD/Applications/
 Utilities/Print Center or Print Setup Utility folder), then choose the printer you want to remove and remove it by clicking the "Delete" button.
- Click on the model name of your Brother product in the printer list. From the Finder menu, delete the Printer.
- Drag the "Brother" folder
 (Macintosh HD/Library/Printers/Brother)
 into the Trash bin.
- Delete the "Brother TWAIN.ds" folder (Macintosh HD/Library/Image Capture/ TWAIN Data Sources/Brother TWAIN.ds).
- Reboot the Mac.
- 9 Log on as an "Administrator".
- 10 Empty the trash bin.




The MFL-Pro SUite, Brother printer driver, scanner driver and Brother ControlCenter2 has been uninstalled and the uninstallation is now complete.

Consumables and Options



Optional memory

The machine has the following optional accessories. You can expand the capabilities of the machine by adding more memory.



You can expand the memory by installing a (144-pin SO-DIMM) memory module. Please refer to Chapter B of User's Guide for more details.



Consumables

When the time comes to replace consumable items, an error message will be indicated on the LCD. For more information about the consumables for your machine, visit us at http://solutions.brother.com/ or contact your local Brother reseller.

Toner Cartridge	Drum Unit	
<standard toner=""> TN-150C/TN-150M/TN-150Y/TN-150BK <high-yield toner=""> TN-155C/TN-155M/TN-155Y/TN-155BK</high-yield></standard>	DR-150CL	
Belt Unit (BU-100CL)	Waste Toner Box (WT-100CL)	

Trademarks

The Brother logo is a registered trademark of Brother Industries, Ltd.

Brother is a registered trademark of Brother Industries, Ltd.

Multi-Function Link is a registered trademark of Brother International Corporation.

Microsoft, Windows and Windows Server are registered trademarks of Microsoft Corporation in the United States and/or other countries.

Windows Vista is either a registered trademark or a trademark of Microsoft Corporation in the United States and other countries

Macintosh and True Type are registered trademarks of Apple Inc.

Nuance, the Nuance logo, PaperPort and ScanSoft are trademarks or registered trademarks of Nuance Communications, Inc. or its affiliates in the United States and/or other countries.

Presto! PageManager is a registered trademark of NewSoft Technology Corporation.

Each company whose software title is mentioned in this manual has a Software License Agreement specific to its proprietary programs.

All other brand and product names mentioned in this manual are trademarks or registered trademarks of their respective companies.

Compilation and Publication

Under the supervision of Brother Industries Ltd., this manual has been compiled and published, covering the latest product descriptions and specifications.

The contents of this manual and the specifications of this product are subject to change without notice.

Brother reserves the right to make changes without notice in the specifications and materials contained herein and shall not be responsible for any damages (including consequential) caused by reliance on the materials presented, including but not limited to typographical and other errors relating to the publication.

This product is designed for use in a Professional Environment.

© 2007 Brother Industries, Ltd. © 1998-2008 TROY Group, Inc. © 1983-2008 PACIFIC SOFTWORKS INC. This product includes the "KASAGO TCP/IP" software developed by Elmic Systems, Inc. Portions Copyright for ICC profiles 2003 by European Color Initiative, www.eci.org. ALL RIGHTS RESERVED.

