Quick Setup Guide Start Here



Please read the Product Safety Guide first before you set up your machine. Then, please read this Quick Setup Guide for the correct setup and installation.

WARNING

WARNING indicates a potentially hazardous situation which, if not avoided, could result in death or serious injuries.



Unpack the machine and check the components

The components included in the box may differ depending on your country.



WARNING

- Plastic bags are used in the packing of your machine. To avoid danger of suffocation, keep these plastic bags away from babies and children. Plastic bags are not toys.
- Only use the power cord supplied with this product.
- To ensure safe operation the supplied plug must be inserted only into a standard power outlet that is properly grounded through the standard electrical wiring. Non grounded equipment may cause an electrical shock hazard, and may cause excessive electrical noise radiation.

🖉 Note

- We recommend that you save the original packaging in case you must ship your machine.
- Please use the supplied USB cable if you wish to connect the machine to a computer.

USB cable

It is recommended to use a USB 2.0 cable (Type A/B) that is no more than 2 metres long.

Network cable

Use a straight-through Category5 (or greater) twisted-pair cable for 10BASE-T or 100BASE-TX Fast Ethernet Network.

- Remove the protective tape and film covering the machine and the LCD.
- Make sure you have all the components.



Connect the power cord

Important

DO NOT connect the USB cable yet.

a

b

Connect the power cord.

WARNING

The machine must be fitted with an earthed plug.



Open the Top Cover 1.



C Pull the Output Tray out of the machine **1** and then unfold the Document Stopper **2**.







- Swipe up or down, or press ▲ or ▼ to display Initial Setup. Press Initial Setup.
- **C Press** Local Language.
- C Swipe up or down, or press ▲ or ▼ to display your language. Press your language.





Set the date and time

The machine displays the date and time.

- C Press Date & Time.
- **Press** Date.
- Enter the last two digits of the year on the Touchscreen, and then press OK.
- Repeat for month and day.
- **9** Press Time.
- **1** Enter the time on the Touchscreen in 24-hour format, then press OK.
- Press 🚮



Automatic Daylight Savings Time

You can set the machine to change automatically for daylight savings time. It will reset itself forward one hour in the spring and backward one hour in the fall.

🖉 Note

This function is not available for some countries.

- Press III.
- Swipe up or down, or press ▲ or ▼ to display Initial Setup. Press Initial Setup.
- C Press Date & Time.
- **O Press** Auto Daylight.
- Press On (or Off).
- f Press 🚮.



Set Daylight Saving Time

You can set the machine to change for Daylight Saving Time. If you choose Forward Hour, it will reset the time forward one hour and if you choose Backward Hour, it will reset the time backward one hour.

Note

This function is not available for some countries.

- C Press Date & Time.
- **O Press** Daylight Save.
- **Press** Forward Hour **or** Backward Hour.
- f Press 🚮.



Set the Time Zone

You can set the time zone (not summer time but standard time) on the machine for your location.

a	Press 🛐 .
b	<pre>Swipe up or down, or press ▲ or ▼ to display Initial Setup. Press Initial Setup.</pre>
С	Press Date & Time.
d	Press Time Zone.
e	Enter your time zone. Press OK.
f	Press 👩.



Choose your connection type

These installation instructions are for Windows[®] XP Home, XP Professional, Windows Vista[®], Windows[®] 7, and Mac OS X v10.6.x and 10.7.x.

🖉 Note

If your computer does not have a DVD-ROM drive you can download the latest drivers, manuals and utilities for your model from the Brother Solutions Center at <u>http://solutions.brother.com/</u>. Some software applications included on the DVD-ROM may not be available as a download.





For USB interface cable

Windows[®], go to page 6 Macintosh, go to page 8





For Wired Network

Windows[®], go to page 10 Macintosh, go to page 13



For Wireless Network

Windows $^{\ensuremath{\mathbb{R}}}$ and Macintosh, go to page 16





For USB interface users

(Windows[®] XP Home/XP Professional/Windows Vista[®]/Windows[®] 7)



Make sure that your computer and machine are on and you are logged on with Administrator rights.

Important

- DO NOT connect the USB cable yet.
- If there are any programs running, close them.

🖉 Note

- The screens may differ depending on your operating system.
- The DVD-ROM includes Nuance[™] PaperPort[™]12SE. This software supports Windows[®] XP Home (SP3 or greater), XP Professional (SP3 or greater), Windows Vista[®] (SP2 or greater) and Windows[®] 7. Update to the latest Windows[®] Service Pack before installing MFL-Pro Suite.



Put the supplied DVD-ROM into your DVD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.

🖉 Note

If the Brother screen does not appear automatically, go to **Computer (My Computer)**, double-click the DVD-ROM icon, and then double-click **start.exe**. The DVD-ROM Top Menu will appear. Click Install MFL-Pro Suite and click Yes if you accept the license agreements. Follow the on-screen instructions.

Adobe Flash Player 10	brothe
	Cione
Top Menu	
Full Driver & Software Package (Includes Wireless & Wired Networ	The multifunction drivers and Nuance (TM) PaperPort(TM) SE are automatically installed.
User's Guides	
Custom Installation	
Additional Applications	
Brother Support	
On-Line Registration	
© 2001-2012 Brother Industries, Ltd. All Rights Reser	Ned 5 Back + Exit

🖉 Note

For Windows Vista[®] and Windows[®] 7, when the User Account Control screen appears, click **Continue** or **Yes**.

C Choose Local Connection (USB), and then click Next. The installation continues.

Brother Device Installation	
Connection Type	
Select the connection type of the device yo cannot use the wired and wireless network	au want to install, and then click Next. You at a time.
Local Connection (USB)	
📰 Custom Install	
Wired Network Connection (Ethernet)	
Custom Install	- Seed
Wireless Network Connection	
Custom Install	
nstallShield	
	Cancel

🖉 Note

d

For Windows Vista[®] and Windows[®] 7, when the Windows[®] Security screen appears, click the check box and click **Install** to complete the installation correctly.



When this screen appears, go to the next step.









Connect the USB cable

Connect the USB cable to the USB port marked with a symbol on your machine, and make sure to connect the other end of the cable to your computer.



The installation will continue automatically.
 Multiple screens will appear during the installation.

Important

DO NOT cancel any of the screens during the installation. It may take a few seconds for all screens to appear.

C When the On-Line Registration screen is displayed, make your selection and follow the on-screen instructions.



а

Finish and restart

Click **Finish** to restart your computer. After restarting the computer, you must log on with Administrator rights.

Brother Device Installation	
	Brother Software Suite Installation Completed! The InstallShield Wized has successfully installed Brother Software Suite. Before you can use the program, you must restart your computer.
	Yes, I want to restart my computer now
	No, I will restart my computer later.
	If your machine has a USB device inserted into the USB interface (on the right side), please make sure to remove it before restarting Windows.
	<back cancel<="" finish="" th=""></back>

🖉 Note

• If an error message appears during the software installation, run the **Installation**

Diagnostics located in (Start)/ All Programs/Brother/ADS-2600W.

• Depending on your security settings, a Windows[®] Security or antivirus software window may appear when using the machine or its software. Please allow or permit the window to continue.

The following screens will appear.

- When the **Software Update Setting** screen appears, choose the software update setting you want and click **OK**.
- When the Brother Product Research & Support Program starts up, follow the on-screen instructions.

🖉 Note

Internet access is required for the software update and the Brother Product Research & Support Program.



The installation is now complete.

Now go to

Proceed to Install Optional Applications on page 33.

USB



For USB interface users (Mac OS X v10.6.x, 10.7.x)



Before you install

Make sure your machine is connected to the power and your Macintosh is on. You must be logged on with Administrator rights.

Note

For Mac OS X v10.5.x users, upgrade to Mac OS X v10.6.x - 10.7.x before installation.



Connect the USB cable

• Important

- DO NOT connect the machine to a USB port on a keyboard or a USB hub.
- Connect the machine directly to your Macintosh.
- a Connect the USB cable to the USB port marked with a 😽 symbol on your machine, and make sure to connect the other end of the cable to your computer.





b

Install MFL-Pro Suite

- a Put the supplied installer DVD-ROM into your DVD-ROM drive.
 - Double-click the Start Here OSX icon to install. If the model name screen appears, choose your machine.



- С
 - Choose Local Connection (USB), and then click Next. Follow the on-screen instructions.

Connection Type			
elect the connection ty	pe of the device you want to ins	tall, and then click Nex	t.
Wireless Network	Connection		
- Wileless Network	connection		
Local Connection Wired Network Co	(USB) nnection (Ethernet)	1	

- d Please wait for the software to install. After the installation, the Brother software will search for the Brother device. This will take a few moments to complete.
- е Choose your machine from the list, and then click Next.

0	Setup	Wizard	
oose the devi	ce you want to	install	
loose the devi	ce you want to	instan	
te: If you want to add	d your machine manual	ly, click the "Custom" butto	in.
/		Take 10 Process	
other ADS-X000X	USB		
F.*			
			A.
Custom		Cancel	Next



The installation of MFL-Pro Suite is now complete. Go to step 12.







Click Presto! PageManager or Presto!
 BizCard and follow the on-screen instructions.

00	Setup Wizard
Content Support Press PapelAnager is a powerlad Social and the second	Senge Wood Image Preson PageManager Image Page Page Page Page Page Page Page P
	On-Line Registration
	Supplies Information
	Cancel Next



The installation is now complete.

For wired network interface users

(Windows[®] XP Home/XP Professional/Windows Vista[®]/Windows[®] 7)



Before you install

Make sure that your computer and machine are on and you are logged on with Administrator rights.

Important

If there are any programs running, close them.

🖉 Note

- The screens may differ depending on your operating system.
- The DVD-ROM includes Nuance[™] PaperPort[™] 12SE. This software supports Windows[®] XP Home (SP3 or greater), XP Professional (SP3 or greater), Windows Vista[®] (SP2 or greater) and Windows[®] 7. Update to the latest Windows[®] Service Pack before installing MFL-Pro Suite.
- If you have previously set up your machine for a wireless network and then want to set it up on a wired network, you should check that the machine's Wired Enable is set to On. The wireless network interface will become inactive with this setting.

On your machine, press and Network. Swipe up or down, or press ▲ or ▼ to display Wired LAN, and then press Wired LAN. Swipe up or down, or press ▲ or ▼ to display Wired Enable, and then press Wired Enable. Press On.

Press 📶



Connect the network cable

You will find the Ethernet port marked with a symbol on the back of the machine as shown below. Remove the protective cap and connect the network cable to the Ethernet port.



Connect the cable to your network.





Wired Network

Windows[®]



a

Install MFL-Pro Suite

Put the supplied DVD-ROM into your DVD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.

🖉 Note

If the Brother screen does not appear automatically, go to **Computer (My Computer)**, double-click the DVD-ROM icon, and then double-click **start.exe**.

The DVD-ROM Top Menu will appear. Click Install MFL-Pro Suite and click Yes if you accept the license agreements. Follow the on-screen instructions.

brothe
The multifunction drivers and Nuance (TM) PaperPort(TM) SE are automatically installed.

🖉 Note

For Windows Vista[®] and Windows[®] 7, when the User Account Control screen appears, click **Continue** or **Yes**.

C Choose Wired Network Connection (Ethernet), and then click Next.

onnection Type		
Select the connection type of the device you cannot use the wired and wireless network at		all, and then click Next.You
Cocal Connection (USB)		
Custom Install		
Wired Network Connection [Ethernet]		
Custom Install		- Carlos
C Wireless Network Connection		
Custom Install		
/IShield		
	< <u>B</u> ack	Cancel

When this screen appears, choose Change the Firewall port settings to enable network connection and continue with the installation. (Recommended) and click Next.

Brother Device Installation
Firewall/AniVirus detected
Windows Frewall is helping to protect your computer. With the current filterwall settings some of the network features on your machine will not work. In order for all the network features of the machine to work, some of the Windows Friewall poor settings need to be changed.
Change the Firewal port settings to enable network connection and continue with the installation. [Recommended]
Continue without changing the Windows Firewall settings. [Some network features will be disabled]
For AntiVirus Software Users:
If you are using AntiVirus Software, a warning dialog window might appear during the installation, then choose "allow" to continue.
Cancel

If you are using a firewall other than the Windows[®] Firewall or the Windows[®] Firewall is off, this screen may appear.

Brother De	vice Installation
	Notice for AntiVirus Software users: In case you are using an AntiVirus Software, a warning dialog window might appear during the installation. When warning dialog window appears, choose "allow" to continue installing.
	ОК

See the instructions provided with your firewall software for information on how to add the following network ports.

- For network scanning, add UDP port 54925.
- If you still have trouble with your network connection, add UDP port 137 and 161.

🖉 Note

- If your machine is not found over the network, confirm your settings by following the on-screen instructions.
- If there is more than one of the same model connected on your network, the IP Address and Node Name will be displayed to help you identify the machine.



Windows®

The installation of the Brother drivers will automatically start. The installation screens appear one after another.

Important

DO NOT cancel any of the screens during the installation. It may take a few seconds for all screens to appear.

🖉 Note

For Windows Vista[®] and Windows[®] 7, when the Windows[®] Security screen appears, click the check box and click **Install** to complete the installation correctly.

When the **On-Line Registration** screen is displayed, make your selection and follow the on-screen instructions.



Finish and restart

Click Finish to restart your computer. After restarting the computer, you must log on with Administrator rights.



🖉 Note

If an error message appears during the software installation, run the Installation Diagnostics

located in (Start)/All Programs/Brother/ ADS-2600W LAN.

- The following screens will appear.
 - When the **Software Update Setting** screen appears, choose the software update setting you want and click **OK**.
 - When the Brother Product Research & Support Program starts up, follow the on-screen instructions.

🖉 Note

b

Internet access is required for the software update and the Brother Product Research & Support Program.

3 Install MFL-Pro Suite on additional computers (if necessary)

If you want to use your machine with multiple computers on the network, install MFL-Pro Suite on each computer. Go to step **11** on page 11. Also see step **9** on page 10 before you install.

🖉 Note

Network license (Windows®)

This product includes a PC license for up to 2 users. This license supports the installation of the MFL-Pro Suite including Nuance™ PaperPort™ 12SE on up to 2 PCs on the network. If you want to use more than 2 PCs with Nuance™ PaperPort™ 12SE installed, please purchase the Brother NL-5 pack which is a multiple PC license agreement pack for up to 5 additional users. To purchase the NL-5 pack, contact Brother customer service or your local Brother dealer.



The installation is now complete.

Now go to Proceed to Install Optional Applications on page 33.



For wired network interface users (Mac OS X v10.6.x, 10.7.x)



Before you install

Make sure your machine is connected to the power and your Macintosh is on. You must be logged on with Administrator rights.

🖉 Note

- For Mac OS X v10.5.x users, upgrade to Mac OS X v10.6.x - 10.7.x before installation.
- If you have previously set up your machine for a wireless network and then want to set it up on a wired network, you should check that the machine's Wired Enable is set to On. The wireless network interface will become inactive with this setting.

On your machine, press ∭ and Network. Swipe up or down, or press ▲ or ▼ to display Wired LAN, and then press Wired LAN. Swipe up or down, or press ▲ or ▼ to display Wired Enable, and then press Wired Enable. Press On.

Press 🚮

Connect the network cable

You will find the Ethernet port marked with a symbol on the back of the machine as shown below. Remove the protective cap and connect the network cable to the Ethernet port.



Connect the cable to your network.

b





Install MFL-Pro Suite

- Put the supplied installation DVD-ROM into your DVD-ROM drive.
- Double-click the **Start Here OSX** icon to install. If the model name screen appears, choose your machine.



C Choose Wired Network Connection (Ethernet), and then click Next. Follow the on-screen instructions.

0	Start Here OSX		
Connection Typ			
elect the connection	ype of the device you want to install.	, and then click Next.	
Wireless Network	Connection	-	
Local Connection	n (USB)		
Wired Network C	onnection (Ethernet)		~
	Cancel	Back	lext

- C Please wait for the software to install. After the installation, the Brother software will search for the Brother device. This will take a few moments to complete.
- If the machine is configured for your network, choose your machine from the list, and then click Next.

00	Setup Wizard		
Choose the devic	e you want to install		
Note: If you want to add	your machine manually, click the	"Custom" button.	
Device	* Connection	P address	
Brother ADS-2500W	Network	3002002200	
SIGNEL ADD-23001	THETHORY	~~~~~~	
☆ -			
		_	
Custom		Cancel	ext

🖉 Note

- If your machine is not found over the network, confirm your network settings.
- You can find your machine's MAC Address (Ethernet Address) and IP Address from the control panel of the machine.
- If this screen appears, enter a name for your Macintosh up to 15 characters long, and then click Next.

Setup Netwo	rk "Scan to" name
Register your com computer will app	puter with the machine to enable the Network "Scan to" functions. Your ear when the "Scan to" options on the machine are selected. (Recommended).
This name will a	ppear when the "Scan to" menu is selected at the machine.
	Cancel

The name you enter will appear on the machine's LCD when you choose a scan option. (➤>User's Guide: Scan from the Control Panel of the Machine)

1			
1	ി	k	2
	$ \cdot $	LD	`

The installation of MFL-Pro Suite is now complete. Go to step **12**.



Macintosh



a

Install Presto! PageManager and Presto! BizCard

Click **Presto! PageManager** or **Presto! BizCard** and follow the on-screen instructions.

000	Setup Wizard
Brother Support Brother Support document management application for business or personal needs. With the new document and file management locit, Radioty and management locit, Radioty and	Preso PageManager
	Prother Web Connect On-Line Registration Brother Solutions Center
	Supplies Information
	Cancel Next



If you want to use your machine with multiple computers on the network, install MFL-Pro Suite on each computer. Go to step **11** on page 14. Also see step **9** on page 13 before you install.



The installation is now complete.



For wireless network interface users



Before you begin

First you must configure the wireless network settings of your machine to communicate with your network access point/router. After the machine is configured to communicate with your access point/router, computers on your network will have access to the machine. To use the machine from these computers, you will need to install the drivers and software. The following steps will guide you through the configuration and installation process.

To achieve optimum results with normal everyday document scanning, place the Brother machine as close to the network access point/router as possible with minimal obstructions. Large objects and walls between the two devices as well as interference from other electronic devices can affect the data transfer speed of your documents.

Due to these factors, wireless may not be the best method of connection for all types of documents and applications.

Although your Brother machine can be used in both a wired and wireless network, only one of the connection methods can be used at a time.

🖉 Note

If you have previously configured the wireless settings of the machine you must reset the network settings before you can configure the wireless settings again.

On your machine, press **]]** and Network.

Swipe up or down, or press ▲ or ▼ to display Network Reset, and then press Network Reset. Press Yes to accept. Hold down Yes for 2 seconds to confirm.

The following instructions are for infrastructure mode (connected to a computer through an access point/router). **Infrastructure Mode**



Access point/router

- Wireless Network machine (your machine)
- Wireless capable computer connected to the access point/router
- Wired computer connected to the access point/router
- Mobile Device connected to the wireless access point/router

Please make sure the wireless network settings of the machine match the access point/router.

🖉 Note

To set up your machine in Ad-hoc mode (connected to a wireless capable computer without an access point/router) you can find instructions in the Network User's Guide on the DVD-ROM. You can view the Network User's Guide by following the instructions below.

1 Turn on your computer. Insert the DVD-ROM into your DVD-ROM drive.

For Windows[®]:

- 2 Choose your model and the language. The DVD-ROM top menu will appear.
- 3 Click User's Guides, and then click HTML documents. The top page will appear.
- 4 Click Network User's Guide.

For Macintosh:

- 2 Double-click **User's Guides**. Choose your model and the language.
- 3 Click User's Guides.





Choose your wireless setup method

The following instructions will offer three methods for setting up your Brother machine on a wireless network. Choose the method you prefer for your environment.









(ຈາງ For Wireless Network Users



Rote

This example shows Windows[®] installation. For Mac installation, insert the installation DVD-ROM into your DVD-ROM drive and double-click **Start Here OSX** to install. Select Wireless installation and follow the Wireless Device Setup instructions on your computer screen.

You need to temporarily use a USB cable during configuration.

Put the supplied DVD-ROM into your DVD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.

🖉 Note

If the Brother screen does not appear automatically, go to **Computer (My Computer)**, double-click the DVD-ROM icon, and then double-click **start.exe**.

The DVD-ROM Top Menu will appear. Click Install MFL-Pro Suite and click Yes if you accept the license agreements. Follow the on-screen instructions.



🖉 Note

For Windows Vista[®] and Windows[®] 7, when the User Account Control screen appears, click **Continue** or **Yes**.

C Choose Wireless Network Connection, and then click Next.

Connection Type	
Select the connection type of the device you cannot use the wired and wireless network at	want to install, and then click Next.You a time.
Cocal Connection (USB)	
Custom Install	- Color
C Wired Network Connection (Ethernet)	~~~
Custom Instal	and the
Wireless Network Connection	
Custom Install	
tall5hield	<back next=""> Cancel</back>

C When this screen appears, choose Change the Firewall port settings to enable network connection and continue with the installation. (Recommended) and click Next.

Brother Device Installation	
Firewall/AntiVirus detected	
Windows Fiewall is helping to protect your computer. With the current firewall settings some of the network features on your mac In order for all the network leatures of the machine to work, some of the W settings need to be changed.	hine will not work. indows Firewall port
 Change the Firewal port settings to enable network connection and co installation. (Recommended) 	
 Continue without changing the Windows Firewall settings. (Some network disabled) 	irk features will be
For AntiVirus Software Users:	
It you are using Anti/nuc Software, a warring dateg window might appear installation, then choose "allow" to continue.	
< Back Next>	Cancel

If you are using a firewall other than the Windows[®] Firewall or the Windows[®] Firewall is off, this screen may appear.

Brother De	zvice Installation
	Notice for AntVirus Software users: In case you are using an AntVirus Software, a warning dialog window might appear during the installation. When warning dialog window appears, choose "allow" to continue installing.
	Οκ

See the instructions provided with your firewall software for information on how to add the following network ports.

- For network scanning, add UDP port 54925.
- If you still have trouble with your network connection, add UDP port 137 and 161.





Choose Yes, I have a USB cable to use for

🖉 Note

e

For instructions on connecting the USB cable to the USB port of your machine, see Connect the USB cable on page 7. **G** When the following screen appears, check **Yes** if you want to connect to the listed SSID. Click **Next** and go to **j**.

Wireless Device Setup Wizard
Detecting existing wireless network settings on your Computer
The wireless network settings of your computer or wireless access point have been detected.
The wireless network name detected (Wireless Access Point/Router name): SSID: YBBUser
Solu. Todoven Would you like to connect to the wireless network using these settings?
© Yes © No
Next > Cancel

When the following screen appears, the wizard will search for wireless networks available to your machine. Choose the SSID that you wrote down for your network in step **10-a** on page 17, and then click **Next**.

vailable Wireless N	etworks	((<u>ر</u> رو
hoose the SSID that you che	cked in advance.			
		Where is	my SSID?	
N (0.000)	a			
Itte YBBUser	5	802.11b/g/n		
		www.rrw(rimapa)		_
100 PCAPL2	9	802.11b/g (11Mbps)	'54Mbps) 🔳 🔳 🗌	1
10.00 NETGDEV23	11	802 11b/a (11Mbos)	64Mhoc) -	
Refresh	Access Poir Station	nt/Base ⊐\$≹t	□ Ad-hoc Networ	k
appea	r in this list, or if	on of your Wireless Acc you are hiding it, you n the 'Advanced' button.		
Help		Back Next >	Canc	

🖉 Note

- If the list is blank, check that the access point has power and is broadcasting the SSID, and then see if the machine and the access point are within range for wireless communication. Then click **Refresh**.
- If your access point is set to not broadcast the SSID you can manually add it by clicking the **Advanced** button. Follow the on-screen instructions for entering the **Name (SSID)**, and then click **Next**.

Wireless Device Setup Wizard		
Wireless Network Name		ஞ
Configure the wireless network name that	the device will be associated with.	
Name(SSID)		
☐ This is an Ad-hoc network	and there is no access point.	
Shannel	1 *	
Help	< Back	Cancel

For Wireless Network Users

Enter the **Network Key** you wrote down in step **10-a** on page 17, and then click **Next**.

etwork Key Configuration	((((())))
ase enter the network security key whi	ch you checked earlier.
	Where is my network key?
	where is my network key?
Network Key	ABCDEF1234
in the second Automic and	Francisco to a colling to the data and Marcad
ur wireless network Authentication and ad to enter the Network Key.	Encryption type will automatically be detected. You only
	Encryption type will automatically be detected. You only
	Encryption type will automatically be detected. You only
	Encryption type will automatically be detected. You only
	Encryption type will automatically be detected. Yo

🖉 Note

If your network is not configured for Authentication and Encryption, the following screen will appear. To continue configuration, click **OK** and go to **j**.

Wireless Device Setup Wizard
Name (SSID) :HELLO
This Wireless Network is not a ver. It is not using secure authentic tion and noryption. Do you want to contin
OK Cancel

Click **Next**. The settings will be sent to your machine.



🖉 Note

- The settings will remain unchanged if you click **Cancel**.
- If you want to manually enter the IP address settings of your machine, click Change IP Address and enter the necessary IP address settings for your network.
- If the wireless setup failure screen appears, click **Retry** and try starting from step **h** again.

Disconnect the USB cable between the computer and the machine.

Nireless Device Setup Wizard
Disconnecting Your Device and Your Computer
Please disconnect the USB cable between your computer and the device.
Ned > Cancel

Click Next to continue to install MFL-Pro Suite.



To install MFL-Pro Suite

For Windows[®] users:

Now go to

Step 13-e on page 29

For Macintosh users:



Step 13-d on page 31



Manual setup from the control panel using the Setup Wizard (Macintosh, mobile devices and Windows[®])

You cannot configure an enterprise wireless network using the Setup Wizard from the control panel. If you choose the SSID for configuring an enterprise wireless network after searching the available SSIDs, the message dialog about Enterprise Authentication Method will appear.

To configure an enterprise wireless network, use installer DVD-ROM and follow the instructions.

a Press 🛐 .

Swipe up or down, or press ▲ or ▼ to display Network, and then press Network. Swipe up or down, or press ▲ or ▼ to display WLAN, and then press WLAN. Swipe up or down, or press ▲ or ▼ to display

Setup Wizard, and then press Setup Wizard.

When Enable WLAN? is displayed, press Yes to accept.

This will start the wireless setup wizard. To cancel, press No.

The machine will search for available SSIDs. It will take several seconds to display a list of available SSIDs.

If a list of SSIDs is displayed, swipe up or down, or press ▲ or ▼ to choose the SSID you wrote down in step **10-b** on page 18. Select the SSID you want to connect with, then press OK.

If the wireless access point/router of the selected SSID supports WPS and the machine asks to use WPS, go to **c**. If the machine asks you to enter a Network Key, go to **d**. Otherwise, go to **e**.

🖉 Note

b

- If a list of SSIDs is not displayed, make sure your access point is on. Move your machine closer to the access point and try starting from **a** again.
- If your access point is set to not broadcast the SSID, you will have to manually add the SSID name. For details, see the Network User's Guide.

C Press Yes to connect your machine using WPS. (If you choose No (Manual) to continue manual configuration, go to **d** to enter a Network Key.)

When the LCD shows Start WPS, press the WPS button on your wireless access point/router, and then press Next to proceed. Go to **e**.

Enter the Network Key you wrote down in step **10-b** on page 18 using the Touchscreen.

Press Trans to cycle between lower case and

upper case. Press ▲ 1 @ to cycle between letters, numbers and special characters. (The characters available may differ depending on your country.) To move the cursor to the left or right, press ◀ or ►.

(For more information, see *Entering Text for Wireless Settings* on page 35.)

Press OK when you have entered all the characters, then press Yes to apply your settings.

• Your machine will now try to connect to your wireless network. It may take a few minutes.

- A connection result message appears until the OK button is pressed on the LCD. If your wireless device is connected successfully, the LCD shows Connected. If the connection failed, the LCD shows an error code. Make a note of the error code, see *Troubleshooting* on page 25, and correct the error.
- Wireless setup is now complete. A four level indicator at the top of your machine's LCD will show the wireless signal strength of your access point/router.

To install MFL-Pro Suite, continue to step **12**.

For Windows[®] users:

Now go to

Page 28

For Macintosh users:

Now go to

Page 31



🖉 Note

For Mobile Device users, please go to the User's Guide for the application you are using (e.g. Brother iPrint&Scan or other applications) for additional details on how to use your machine with the application. To download the User's Guide for the application you are using, please go to the manuals download section on your model's home page on the Brother Solutions Center at http://solutions.brother.com/.





Confirm your wireless access point/router has the WPS or AOSS[™] symbol as shown below.



Place the Brother machine within range of your WPS or AOSS[™] access point/router. The range may differ depending on your environment. Refer to the instructions provided with your access point/router.

C Press 🏢

Swipe up or down, or press ▲ or ▼ to display Network, and then press Network. Swipe up or down, or press ▲ or ▼ to display WLAN, and then press WLAN.

Swipe up or down, or press ▲ or ▼ to display WPS/AOSS, and then press WPS/AOSS.

When Enable WLAN? is displayed, press Yes to accept.

🖉 Note

If your wireless access point/router supports WPS (PIN Method), you can also configure your machine using the PIN (Personal Identification Number) Method. ➤>Network User's Guide: Configuration using the PIN Method of WPS (Wi-Fi Protected Setup)



When the LCD shows to start WPS or AOSS[™], press the WPS or AOSS[™] button on your wireless access point/router. See the user's guide of your wireless access point/router for instructions.



Then press OK and your machine will now automatically detect which mode (WPS or AOSS[™]) your wireless access point/router uses and try to connect to your wireless network. A connection result message appears until the OK button is pressed on the LCD. If your wireless device is connected successfully, the LCD shows Connected. If the connection failed, the LCD shows an error code. Make a note of the error code, see *Troubleshooting* on page 25, and correct the error.



Wireless setup is now complete. A four level indicator at the top of your machine's LCD will show the wireless signal strength of your access point/router.

To install MFL-Pro Suite, continue to step **12**.

For Windows[®] users:

Now go to

Page 28

For Macintosh users:

Now go to

Page 31

Troubleshooting

Please do not contact Brother Customer Service for assistance without the wireless security information. We cannot assist you in locating your network security settings.

How can I find the wireless security information (SSID and Network Key)

1) You should see the documentation provided with your wireless access point/router.

2) The default SSID could be the manufacturer's name or the model name.

- 3) If you do not know the security information, please consult the router manufacturer, your system administrator, or internet provider.
- * The Network Key may also be described as the Password, Security Key or Encryption Key.
- * If the WLAN access point/router is not broadcasting the SSID, the SSID will not automatically be detected. You will have to manually enter the SSID name. See *Configuring your machine when the SSID is not broadcasting* in the *Network User's Guide*.

Error codes

If the LCD shows an error code in the table below, refer to the following instructions and correct the error.

Error code	Recommended Solutions
	The wireless setting is not activated, turn the wireless setting to ON.
	- If a network cable is connected to your machine, disconnect it and turn the wireless setting of your machine to ON.
TS-01	1. On your machine, press 👔 and Network.
	2. Press WLAN, and then Setup Wizard.
	3. When Enable WLAN? is displayed, press Yes. This will start the wireless setup wizard.
	The wireless access point/router cannot be detected.
	1. Check the following 4 points.
	 Make sure that the wireless access point/router is powered on. Move your machine to an obstruction-free area, or closer to the wireless access point/router.
	 Temporarily place your machine within about one metre from the wireless access point when you are configuring the wireless settings.
TS-02	 If your wireless access point/router is using MAC address filtering, confirm the MAC address of the Brother machine is allowed in the filter.
	 If you manually entered the SSID and security information (SSID/authentication method/encryption method/Network Key), the information may be incorrect. Reconfirm the SSID and security information and re-enter the correct information as necessary.
	See How can I find the wireless security information (SSID and Network Key) on page 25 to confirm.



	The wireless network and securi Reconfirm the wireless network * Check if the entered or selecte	settings.			
TS-03	method/UserID/Userpass are		rencryption		
	See <i>How can I find the wireless</i> confirm.	security information (SSID and	Network Key) on page 25 to		
	The Authentication/Encryption m not supported by your machine.	ethods used by the selected win	reless access point/router are		
	For infrastructure mode, change access point/router. Your machine supports the follow		tion methods of the wireless		
	authentication method	encryption method			
	WPA-Personal	TKIP	_		
	WPA2-Personal	AES AES	_		
TC 04	WPA2-Personal	WEP	_		
TS-04	Open	None (without encryption)	-		
	Shared key	WEP	-		
	If your problem is not solved, the SSID or network settings you entered may be incorrect. Reconfirm the wireless network settings.				
	See How can I find the wireless security information (SSID and Network Key) on page 25 to confirm.				
	For ad-hoc mode, change the au the wireless setting. Your machine supports Open au				
TS-05	The security information (SSID/N Reconfirm the SSID and security If your router uses WEP encrypt machine supports the use of the	y information (Network Key). ion, enter the key used as the t	first WEP key. Your Brother		
	See <i>How can I find the wireless</i> confirm.		Network Key) on page 25 to		
	The wireless security information incorrect. Reconfirm the wireless security Network Key) in the table of TS-	information (Authentication me			
TS-06	If your router uses WEP encrypt machine supports the use of the	ion, enter the key used as the t	first WEP key. Your Brother		
	See How can I find the wireless confirm.	security information (SSID and	Network Key) on page 25 to		

For Wireless Network Users

	The machine cannot detect a wireless access point/router that has WPS or AOSS™ enabled.
TS-07	If you would like to configure your wireless settings using WPS or AOSS™, you must operate both your machine and the wireless access point/router. Confirm your wireless access point/router supports WPS or AOSS™ and try starting again.
	If you do not know how to operate your wireless access point/router using WPS or AOSS™ see the documentation provided with your wireless access point/router, ask the manufacturer of your wireless access point/router or ask your network administrator.
TS-08	 Two or more wireless access points that have WPS or AOSS[™] enabled are detected. Confirm that only one wireless access point/router within range has the WPS or AOSS[™] method active and try again. Try starting again after a few minutes in order to avoid interference from other access points.

Note

If the error code TS-20 appears, the machine is still trying to connect to your wireless network. Please wait a few minutes, and then check the WLAN status from the control panel of the machine.



Install the drivers & software

(Windows[®] XP Home/XP Professional/Windows Vista[®]/Windows[®] 7)



Make sure that your computer and machine are on and you are logged on with Administrator rights.

Important

If there are any programs running, close them.

🖉 Note

- The screens may differ depending on your operating system.
- The DVD-ROM includes Nuance[™] PaperPort[™] 12SE. This software supports Windows[®] XP Home (SP3 or greater), XP Professional (SP3 or greater), Windows Vista[®] (SP2 or greater) and Windows[®] 7. Update to the latest Windows[®] Service Pack before installing MFL-Pro Suite.



Install MFL-Pro Suite

Put the supplied DVD-ROM into your DVD-ROM drive. If the model name screen appears, choose your machine. If the language screen appears, choose your language.

Note

If the Brother screen does not appear automatically, go to **Computer (My Computer)**, double-click the CD-ROM icon, and then double-click **start.exe**. The DVD-ROM Top Menu will appear. Click Install MFL-Pro Suite and click Yes if you accept the license agreements. Follow the on-screen instructions.

🗹 Adobe Flash Player 10	
	brother
Top Menu	
Full Driver & Software Package (Includes Wireless & Wired Network Setup)	The multifunction drivers and Nuance (TM) PaperPort(TM) SE are automatically installed.
User's Guides	
Custom Installation	
Additional Applications	
Brother Support	
On-Line Registration	

🖉 Note

b

For Windows Vista[®] and Windows[®] 7, when the User Account Control screen appears, click **Continue** or **Yes**.

C Choose Wireless Network Connection, and





Windows®

When this screen appears, choose Change the Firewall port settings to enable network connection and continue with the installation. (Recommended) and click Next.



If you are using a firewall other than the Windows[®] Firewall or the Windows[®] Firewall is off, this screen may appear.

Â	Notice for AntVirus Software users: In case you are using an AntVirus Software, a warning dialog window might appear during the installation. When warning dialog window appears, choose "allow" to continue installing.	
	OK	

See the instructions provided with your firewall software for information on how to add the following network ports.

- For network scanning, add UDP port 54925.
- If you still have trouble with your network connection, add UDP port 137 and 161.
- Choose your machine from the list, and then click **Next**.

loose the Brother	machine you want	to install		2
Node Name	IP Address	Model Name	Location	Môf ôr
BR X000000	XXXXXXXXXXXXX	ADS-2000W		
•	m			۲
		(Refres	
<	If your device doe the list, please con wireless setting.	(is not appear in nfigure the	Refre: Conligure IP	sh

🖉 Note

- If your machine is not found over the network, confirm your settings by following the on-screen instructions. If you encounter this failure, go to step **10-b** on page 18 and setup the wireless connection again.
- If you are using WEP and the LCD displayed Connected but your machine is not found on the network, make sure you entered the WEP key correctly. The WEP key is case sensitive.

The installation of the Brother drivers will automatically start. The installation screens appear one after another.

Important

DO NOT cancel any of the screens during the installation. It may take a few seconds for all screens to appear.

🖉 Note

g

For Windows Vista[®] and Windows[®] 7, when the

Windows[®] Security screen appears, click the check box and click **Install** to complete the installation correctly.

When the **On-Line Registration** screen is displayed, make your selection and follow the on-screen instructions.



Windows®



Finish and restart

Click Finish to restart your computer. After restarting the computer, you must log on with Administrator rights.



🖉 Note

If an error message appears during the software installation, run the Installation Diagnostics

located in (Start)/All Programs/Brother/ ADS-2600W LAN.

b The following screens will appear.

- When the Software Update Setting screen appears, choose the software update setting you want and click OK.
- When the Brother Product Research & Support Program starts up, follow the on-screen instructions.

🖉 Note

Internet access is required for the software update and the Brother Product Research & Support Program.



Install MFL-Pro Suite on additional computers (if necessary)

If you want to use your machine with multiple computers on the network, install MFL-Pro Suite on each computer. Go to step **12** on page 28.



Network license (Windows[®])

This product includes a PC license for up to 2 users. This license supports the installation of the MFL-Pro Suite including Nuance™ PaperPort™ 12SE on up to 2 PCs on the network. If you want to use more than 2 PCs with Nuance™ PaperPort™ 12SE installed, please purchase the Brother NL-5 pack which is a multiple PC license agreement pack for up to 5 additional users. To purchase the NL-5 pack, contact Brother customer service or your local Brother dealer.



The installation is now complete.

Now go to

Proceed to Install Optional Applications on page 33.

Install the drivers & software (Mac OS X v10.6.x, 10.7.x)



Before you install

Make sure your machine is connected to the power and your Macintosh is on. You must be logged on with Administrator rights.

🖉 Note

For Mac OS X v10.5.x users, upgrade to Mac OS X v10.6.x - 10.7.x before installation.



Install MFL-Pro Suite

- Put the supplied installation DVD-ROM into your DVD-ROM drive.
- Double-click the Start Here OSX icon to install. If the model name screen appears, choose your machine.



C Choose Wireless Network Connection, and then click Next.

00	Start Here OSX		
Connection	Type		
Select the connect	tion type of the device you want to install, a	nd then click Next.	
Wireless Net	work Connection	2	
		•	
O Local Conne Wired Netwo	ction (USB) ork Connection (Ethernet)		
	Cancel	Back Next	



Brother ADS-2600W	Network	202,202,203	
夺 *			

🖉 Note

If your wireless settings fail, the **Wireless Device Setup Wizard** screen appears. Follow the on-screen instructions to complete the wireless configuration.

	Wireless Device Setup	o Wizard	
Wireless Device	ietup		ලා
Using a USB cable tempora installation method.	irily connected to your wireless o	computer is the recomm	ended wireless
Do you have a USB cable	?		
• Yes, I have a USB cal	ole to use for installation.		
from your access p keychain to do it.	ttempt to retreive information oint and requires access to your allow this access if requested.		
O No, I do not have a l	JSB cable.		
Note: If you do not have Method).	a USB cable you can still setup y	our device wirelessly (A	lvanced
	< Back	Next>	Cancel



Macintosh

The installation of the Brother drivers will automatically start. Please wait for the software to install.

🖉 Note

- You can find your machine's MAC Address (Ethernet Address) and IP Address from the control panel of the machine.
- If this screen appears, enter a name for your Macintosh up to 15 characters long, and then click **Next**.

00	Setup Wizard
etup Network	"Scan to" name
	er with the machine to enable the Network "Scan to" functions. Your when the "Scan to" options on the machine are selected. (Recommended).
This name will appe	ear when the "Scan to" menu is selected at the machine.
	brother
	G Set later

The name you enter will appear on the machine's LCD when you choose a scan option. (➤>User's Guide: Scan from the Control Panel of the Machine)

ок!

The installation of MFL-Pro Suite is now complete. Go to step **14**.



a

Click **Presto! PageManager** or **Presto! BizCard** and follow the on-screen instructions.

PageManager and Presto! BizCard

Install Presto!

00	Setup Wizard
rother Support	
Prestol PageManager is a powerful locument management application or business or personal needs. With the new document and file	Prestol PageManager
nanagement tools, it quickly coesses, locates and organizes all te images and scanned documents asily.	Prestol BizCard
	Brother Web Connect
	On-Line Registration
	Brother Solutions Center
	Supplies Information
	Cancel Next



If you want to use your machine with multiple computers on the network, install MFL-Pro Suite on each computer. Go to step **12** on page 31.



The installation is now complete.

Install Optional Applications





Nuance PDF Converter Professional 7

Nuance PDF Converter Professional 7 offers a variety of features for handling PDF files. It can unlock and open PDF files for viewing, editing, annotation and re-assembly.

Enter the Nuance serial number that is shown on the sleeve of the MFL-Pro Suite DVD-ROM package when installing Nuance PDF Converter Professional 7.

NewSoft Presto! BizCard 6

Presto! BizCard lets you manage the information from scanned business cards, such as names, companies, mailing addresses, phone/fax numbers and e-mail addresses, on your computer. Simply scan, or import your business cards and Presto! BizCard automatically saves the data and image for each card. Different viewing modes are available for easy searching, editing, creating, and sorting.

🖉 Note

Make sure you are logged on with Administrator rights.

Open the top menu again by ejecting and then reinserting the DVD-ROM or by double-clicking the start.exe program. If the model name screen appears, choose your machine. If the language screen appears, choose your language.

The DVD-ROM Top Menu will appear. Click Additional Applications.



Click the button for the application you want to install.

Adobe Flash Player 10		
		brothe
Top Menu ≪		
Additional Applications		
Nuance PDF Converter Professional 7		
NewSoft Prestol BizCard 6		
	5 Back	+îj Exit

d

Go back to the **Additional Applications** screen to install more applications.

How to scan to a computer



There are various scanning methods (see *Scanning Methods* in the *User's Guide*). With the following Scan to File feature, you can scan and save documents as PDF files.

To scan documents and configure various settings, please ensure you have installed the driver and connected the machine to your computer by following the instructions in this guide.

- Confirm that the machine is connected to your computer.
- b

Load your document.



- C Swipe left or right, or press < or ► to display Scan 1.
- Press to PC.
- Swipe left or right to select to File and then press OK.
- Select the destination computer you want to save to.
- **9** Press Start. The machine starts to feed and scan your document.

The scanned data is saved in PDF format on the computer that is connected to the machine.

🖉 Note

- You can change Scan to PC settings, such as the saved file format, using ControlCenter. For details, see the User's Guide on the DVD-ROM.
- You can use ControlCenter or the scanner driver to initiate scanning from the computer, as well as save scanned data onto a USB flash memory drive connected to the machine. For details, see the User's Guide on the DVD-ROM.

For Wireless Network Users

Reset the network settings to factory default

To restore all network settings of the internal Scan server to factory default, please follow the steps below.

- a Make sure the machine is not operating, then disconnect all the cables from the machine (except the power cord).
- b Press 🛐
- С Press Network.
- d Swipe up or down, or press ▲ or ▼ to display Network Reset, and then press Network Reset.
- e Press Yes.
- f Hold down Yes for 2 seconds to confirm.
- g The machine will restart, re-connect the cables once this is complete.

Entering Text for Wireless Settings

Press **Trans** to cycle between lower case and upper case.

Press A 1 @ to cycle between letters, numbers and special characters. (The characters available may differ depending on your country.)

To move the cursor to the left or right, press ◀ or ►.



Inserting spaces

To enter a space, press Space button.

Making corrections

If you entered a character incorrectly and want to change it, move the cursor to the incorrect character. Press 🔇 and re-enter the correct character. You can also back up and insert a character.



Trademarks

The Brother logo is a registered trademark of Brother Industries, Ltd.

Brother is a registered trademark of Brother Industries, Ltd.

Windows Vista is either a registered trademark or trademark of Microsoft Corporation in the United States and/or other countries. Windows and Windows Server are registered trademarks of Microsoft Corporation in the United States and/or other countries.

Macintosh and Mac OS are trademarks of Apple Inc., registered in the United States and other countries.

Nuance, the Nuance logo, PaperPort and ScanSoft are trademarks or registered trademarks of Nuance Communications, Inc. or its affiliates in the United States and/or other countries.

AOSS is a trademark of Buffalo Inc.

WPA, WPA2, Wi-Fi Protected Access and Wi-Fi Protected Setup are marks of the Wi-Fi Alliance.

Wi-Fi and Wi-Fi Alliance are registered marks of the Wi-Fi Alliance.

Each company whose software title is mentioned in this manual has a Software License Agreement specific to its proprietary programs.

Any trade names and product names of companies appearing on Brother products, related documents and any other materials are all trademarks or registered trademarks of those respective companies.

Compilation and Publication

Under the supervision of Brother Industries, Ltd., this manual has been compiled and published, covering the latest product descriptions and specifications.

The contents of this manual and the specifications of this product are subject to change without notice.

Brother reserves the right to make changes without notice in the specifications and materials contained herein and shall not be responsible for any damages (including consequential) caused by reliance on the materials presented, including but not limited to typographical and other errors relating to the publication.

Copyright and License

©2012 Brother Industries, Ltd. All rights reserved. This product includes software developed by the following vendors: ©1983-1998 PACIFIC SOFTWORKS, INC. ©2008 Devicescape Software, Inc. This product includes the "KASAGO TCP/IP" software developed by ZUKEN ELMIC,Inc.



